

Pro-Ject Receiver Box

Receiver with FM tuner and remote control



Good sound from sound technology

- Metal case shields the electronics from vibrational and electromagnetic interference
- Bi-Phase PWM-circuit (Pulse Width Modulation)
- Gold plated RCA/Phono sockets and loudspeaker terminals
- Outboard power supply included

Features

- Remote controllable
- Small size allows easy placement
- Two line-level inputs. Optional input expander Pro-Ject Switch Box providing three additional inputs
- 99 Programmable presets. 8 presets with direct access via remote control
- Fine tuning meter, signal strength meter and stereo/mono reception indicator
- Display dimmable
- Pro-Ject Audio digital amplifiers achieve 80% energy efficiency

Technical specifications

Power output:	2 x 20W/30W at 8ohms/4ohms (both channels driven)
Tuning range FM-band:	87,5 - 108,5MHz (50kHz steps)
Programmable presets:	99
THD tuner:	0,05% / Δf 75kHz and f mod 1 kHz
Stereo separation:	30dB / Δf 75kHz and f mod 1 kHz
Sensitivity:	7dB/ μ V mono, 17dB/ μ V stereo /75 ohms
Frequency response:	20Hz - 20kHz ($\pm 0,2$ dB)
Channel separation:	> 40dB at 20kHz
Noise floor:	> -100dB (A weighted)
THD amplifier:	< 0,05% at 10W
Gain:	22dB
Line-level inputs:	1 pair RCA/Phono sockets, 3-pole co-axial 3,5mm \varnothing jack
Input impedance:	20kohms
Antenna input:	1 x co-axial DIN-socket (75 ohms) / US-model F-socket
Outboard power supply:	20V/3A DC (peak 7A DC), suitable for your country's mains supply
Power consumption:	20V/3A DC
Dimensions W x H x D (D with sockets):	103 x 36 x 103 (122)mm
Weight:	670g without power supply

The manufacturer reserves the right to alter the technical specifications without notice.



Available in silver or black finish