

Pro-Ject Amp Box Mono

Mono power amp



Good sound from sound technology

- Metal case shields the electronics from vibrational and electromagnetic interference
- Bi-Phase PWM-circuit (Pulse Width Modulation)
- Gold plated RCA/Phono sockets and loudspeaker terminals
- Outboard power supply included

Features

- Small size allows easy placement
- Pro-Ject Audio digital amplifiers achieve 80% energy efficiency
- The Amp Box Mono can be switched on & off remotely via a trigger signal. A 45cm long power-on cable is supplied for this purpose
- For bi- or tri amplification use, the preamplifier signal and the remote power-on signal can be relayed to further units

Technical specifications

Power output:	2 x 28W/40W at 8ohms/4ohms
Frequency response:	5Hz - 20kHz / + 0dB, - 0,5dB
Noise floor:	> -100dB / A weighted
THD:	< 0,05% / 10W
Gain:	22dB
Pre in:	1 RCA/Phono socket
Input sensitivity:	1V
Input impedance:	47kohm
Pre out:	1 RCA/Phono socket
Speaker connector:	4mm Ø banana plugs, spade connectors or naked wire
Trigger:	12V DC switching voltage
Trigger in and out:	2-pole co-axial Ø 2,5mm jack
Outboard power supply:	20V/3A DC (peak 7A DC), suitable for your country's mains supply
Power consumption:	20V/3A DC
Dimensions W x H x D (D with sockets):	103 x 36 x 103 (122)mm
Weight:	670g without power supply

The manufacturer reserves the right to alter the technical specifications without notice.



Available in silver or black finish